# ЛЛХ

Superior product line

## KeyPad S Plus Jeweller

Wireless touch keypad with support for encrypted contactless cards and key fobs.



### What's new

Baseline KeyPad Plus Jeweller	Superior <b>KeyPad S Plus Jeweller</b>
Common battery	Enhanced battery
Available for all PROs	Available only for accredited partners

This is the device of the **Superior product line**. Superior products are advanced versions of Jeweller devices. This product line is developed for projects. Only accredited Ajax Systems partners can sell, install, and administer Superior products.

## Contactless authorization

- Ajax Pass and Tag to manage security modes without contact
- DESFire® technology for fast and secure users authorization
- Remote access control



- 3 code types: common keypad code, personal user code, and unregistered user code (for the users who do not have Ajax accounts)
- All codes can be changed remotely in the apps



- Protection against invalid access devices
- Protection against code guessing



- Up to 1,700 m of radio communication in an open space
- Data is encrypted throughout the transmission process



Regular polling to display current device statuses

## Flawless autonomy

- Up to 4.5 years of battery life
- Low battery notifications
- Energizer pre-installed batteries



- Tamper alarm
- Device authentication to prevent spoofing
- Holding screw to secure the device on SmartBracket

### Quick installation and setup

- Pairing with a hub via QR code
- Remote control and configuration in the app
- Effortless installation and replacement

Superior, Fibra, and Baseline product lines are mutually compatible. This opens up numerous possibilities for building systems of any configuration.

#### **Compliance with standards**

EN 50131-3 (Grade 2) PD 6662:2017 INCERT (coming soon) SSF (coming soon) NFA2P (coming soon)

### Compatibility

Hubs

Hub Plus, Hub 2 (2G), Hub 2 (4G), Hub 2 Plus, Hub Hybrid (2G), Hub Hybrid (4G)

Range extenders ReX, ReX 2 Communication with control panel

Jeweller communication technology

Frequency bands 868,0 — 868,6 MHz

**Communication range** up to 1,700 m In an open space

#### Features

Contactless access up to 200 cards and key fobs

Access codes up to 200 codes for users who have Ajax accounts and are linked to the hub.

up to 99 codes for unregistered users who do not have Ajax accounts

1 common code for keypad

Duress code

			<ul> <li>up to 200 personal duress codes for registered users</li> <li>1 common duress code for keypad</li> <li>Function button works as panic button or can mute</li> </ul>
			the Interconnected Fire Alarms
Power supply	Installation	Enclosure	Complete set
Battery	Operating temperature range	Colour	KeyPad S Plus Jeweller
4 × AA battery	from -10°C to +40°C	white, black	4 × AA battery
(pre-installed)	Operating humaidity	Dimonoiono	(pre-installed)
	Operating humidity	Dimensions	SmartBracket mounting panel
Battery life	up to 75%	165 × 113 × 20 mm	Installation kit
up to 3.5 years			Quick start guide
With card and key fob reader		Weight	
enabled.		267 g	

up to 4.5 years	Tamper alarm	
With card and key fob reader		
disabled.		
Manufacturer		
Energizer		



For detailed information, scan the QR code or follow the link:

ajax.systems/support/devices/keypad-s-plus/

support@ajax.systems

- @AjaxSystemsSupport\_Bot
- ajax.systems